

GX-BP-16C-R00

Galaxia headend



GX-BP-16C-R00 digital multi-modulator board is equipped with one RF coaxial output connector (F Female) and is able to create up to **16 digital QAM (Annex A/C) multiplexes**. The multi-modulator is the ideal and efficient transmodulation solution for distributing tuned programs from satellite or terrestrial modules inserted in the **GALAXIA** chassis or available in sharing on the same backplane, also those IPTV multicast input.

NOTE: RJ45 port is reserved for future use.

Technical Chars

- 1 x RF coaxial output (F Female)
- Up to 16 x DVB-C QAM RF output multiplexes
- “Hot-swappable” module
- **WEB interface based headend:** the module is managed through a friendly user HTML web interface to set every single parameter
- **NOTE:** RJ45 port is reserved for future use.

GX-BP-16C-R00		
Code		287642
Outputs		
Output		E2-E69
Output frequency	dB	47-862
Max output level	dBμV	85-106
Level adjustment	dB	0 to 20
MER RF	dB	>40
DVB-T Modulation		
Carriers		-
Guard interval modulation		-
DVB-C Modulation		
Output		16QAM/32QAM/64QAM/128QAM/256QAM
Symbol rate	Mbps	3.6 to 6.9
Specifications		
Connectors		1 x F-female (RF), 1 x RJ45
Programming mode		Web interface
Current consumption	W	22
Operating temperature	°C	-5 to +50
Conformity		EN50083-2

Dimensions and packaging		
Pieces		1
EAN code		8016978106769
Packaging dimensions	mm	315 x 170 x 80
Product dimensions	mm	270 x 115 x 20
Packaging weight	kg	1.5