

## GX-4C2CI-BP-00

Galaxia headend



**GX-4C2CI-BP-00** receiver module is equipped with one RF coaxial input connector (F Female) and two PCMCIA Common Interface slots. The module is able to tune up to **four DVB-C digital QAM multiplexes**, decrypt the scrambled programs through the C.I. slots and share and pool the contents to the **GALAXIA** main chassis.

### Technical Chars

- 1 RF coaxial input connector (**F Female**)
- Tunes up to 4 **DVB-C** multiplexes (**Annex A/C**)
- 2 **PCMCIA Common Interface** slots capable of decoding programs from any of the 4 QAM tuners on board the module
- **"Hot-pluggable"** module
- **On-board WEB interface:** programming of all parameters is easily done via HTML web interface

GX-4C2CI-BP-00		
Code		287644
Input		
Input no.		1 ( 4 Channels)
Input level	dBμV	40-80
Demodulators		DVB-C: 16QAM/32QAM/64QAM/128QAM/256QAM
Input band		47-862
Specifications		
Connectors		1x F-female (RF)
Programming mode		Web interface
Current consumption	W	9.5
Common interface		2 x PCMCIA (Standard EN50221, TS10169)
Operating temperature	°C	-5 to +50
Conformity		EN50083-2
Dimensions and packaging		
Pieces		1
EAN code		8016978106783
Packaging dimensions	mm	330 x 185 x 80
Product dimensions	mm	270 x 115 x 20
Packaging weight	kg	1.5

