

# EX605 | BenQ Smart Projector



XGA | 4,000 Lumens

USB-A x 3 | USB Reader | HID Support | Android 9 | Wi-Fi

## Key Features

- **SmartEco:** A compact and light weight design that features a SmartEco mode which continually adapts the amount of lamp power used based on the content of each projected frame. EX605 also comes equipped with a pre-loaded Smart Dashboard app that calculates real-time cost savings.
- **Android 9 Built-in:** Engage students with interactive quizzes on Kahoot!, share assignments through Google Classroom, or access BenQ AMS for easy content management, all directly from Smart Projector itself.
- **Wireless Mirroring:** Supports Airplay, Miracast, Google casting and BenQ's InstaShare 2. The projector's mirroring settings also allow you to set priorities and preferences for mirrored devices.



## Summary


Introducing EX605, an Android-based smart projector designed specifically for education. This all-in-one 4,000-lumen high brightness smart projector eliminates the need for a separate PC, making digital learning more accessible than ever. Teachers and students can open apps directly on the BenQ EX605, easily accessing online resources in the classroom.




296 (W) x 120 (H) x 232 (D) mm

## What's in the Box

- Wi-Fi Dongle
- Power Cable
- Remote Control incl. AAA batteries
- QSG
- Warranty card



| No. | Connectivity                | Q'ty | Recommendations  |
|-----|-----------------------------|------|--|
| 1   | Audio Out                   | x1   | <ul style="list-style-type: none"> <li>• Connects to classroom speakers</li> <li>• Adjust the volume directly through the projector</li> </ul> |
| 2   | Audio In                    | x1   |  |
| 3   | Monitor Out                 | x1   |  |
| 4   | RS232                       | x1   |  |
| 5   | PC                          | x1   |  |
| 6   | HDMI 1.4                    | x1   | Connects to input sources (e.g., laptop)   |
| 7   | USB-A / 0.9A Power Delivery | x1   |  |
| 8   | USB Mini-B                  | x1   |  |
| 9   | USB-A / 1.5A Power Delivery | x1   | For webcams, PM2.5 sensors, keyboards, mice, or USB drives   |
| 10  | USB-A / 0.9A Power Delivery | x2   | For keyboards, mice, or USB drives   |



| No. | Keypad   | Description  |
|-----|----------|--|
| 1   | Freeze   | Teachers can simply freeze the screen, allowing students to take notes while working on personal tasks on the same computer. |
| 2   | Laser    | Laser pointer  |
| 3   | Wireless | Shortcut key for the Wi-Fi Settings menu   |
| 4   | Browser  | Shortcut key for the Firefox browser<br>(or "Chromium" from Jul. via OTA)  |
|     | Clear    |  |
| 5   | Memory   | Shortcut key for the Clear Memory function   |
|     | Cache    |  |
| 6   | Recent   | Shortcut key for the Recently Used Apps menu   |
| 7   | F1       | Shortcut key for the Wireless Projection menu  |
| 8   | F2       | Shortcut key for the Video Conference menu   |
| 9   | F3       | Shortcut key for the File Manager app  |



# Specification

| BenQ SmartEco Projector            |   |
|------------------------------------|---|
| Light Source                       | Lamp  |
| Light Mode and Lifetime            | Normal: 6,000 hr.; SmartEco: 10,000hr.; LampSave: 15,000 hr.  |
| Product Dimension (W x H x D) (mm) | 296 (W) x 120 (H) x 232 (D)   |
| Net Weight (kg)                    | 2.6 +/- 200g  |
| Other Features                     | SmartEco mode built-in, Smart Dashboard app preloaded   |
| Optical                            |   |
| Brightness                         | 4,000 Lumen   |
| Resolution                         | XGA   |
| Contrast                           | 20,000:1  |
| Native Aspect Ratio                | 4:3 (compatible with 16:10, 16:9, 4:3, Auto, Real)  |
| Installation                       |   |
| Throw Ratio                        | 1.96 – 2.15   |
| Corner Fit                         | No  |
| Keystone Correction                | 1D, Vertical $\pm$ 40 degrees   |
| Zoom                               | Fixed   |
| Lens Shift                         | No  |
| Connectivity                       |   |
| USB-A 2.0                          | x 3 (with power supply and reader capabilities)   |
| HDMI                               | x 1   |
| RJ45 LAN control                   | No  |
| Wireless (built-in)                |   |
| Screen Mirroring                   | Driver Free Airplay & Miracast, Chromecast, InstaShare 2, Casting Permission, Do Not Disturb                |
| Split Screen                       | 4   |
| Others                             |   |
| PC-Less                            | Android 9 built-in; Browser and AMS Cloud Preloaded; Supports WPS Office, Slideshow; Keyboard/Mouse control |
| ITS                                | BenQ Device Management System (DMS Cloud), IAM User Account Management                                      |

